

Creasefield Ltd

Unit I Larchfield Estate Ilminster, Somerset TAI9 0PF T 01460 54800 F 01460 57201 enquiries@creasefield.co.uk creasefield.co.uk

Product # CB18984	Issue #		Origination Date 08/05/2013	Originator Patrick Smith	Page # 1/2
Battery Specification	Nominal Ratings: 10.8v, 57Ah			Composition: 3S3P	

NB: Actual voltage and capacity in use will be affected by various factors, including temperature, discharge rate, charge rate and method (if applicable), end point voltage, history (e.g. past use, storage) etc.



CB18984 WABC2102

The IO-year battery for ABB AquaMaster 3 electromagnetic flowmeters. Designed in partnership with ABB.

Designed, developed and manufactured in the UK, Creasefield Flowmeter Batteries use proven lithium battery technology to offer extended life batteries suitable for long-term deployments with a low total cost of ownership.

Battery Details	N.B: Design life is dependent on usage and environment. Elevated temperatures will shorten battery life.			
Pack	10 Year (Lithium) Cell		Tadiran SL2780	
Design Life ¹	Extended - 10 Years	Commodity Code	85065010	
UN38.3 TI-T8 Tested	Yes	UN Number	UN3090	
Lithium Metal Content	45g	Dangerous Goods Class	Class 9	
Packing Group	Group 2	Labelling	ABB WABC2102 label	
Country of Origin	United Kingdom	Temperature Marking	Laser Etched	

Mechanical Details	N.B: All dimensions and weights are nominal. Creasefield Flowmeter Batteries are designed with a protective case and polyurethane filled enclosure intended to protect the pack against dust and water ingress. Care must be taken to protect the battery, cable and terminals.			
Length	147mm	Leads	1000mm	
Depth	68mm	Connector	Souriau UTS6JC8E4P	
Height	138mm	Case	Grey Plastic Case	
Weight	2.2Kg	Encapsulation	Polyurethane	
Dust Protection	Dust-tight	Liquid Protection	Protected against immersion	

Electrical Details	Unit	Nominal	Minimum	Maximum
Discharge Current	mA	12		960
Cut-off Voltage	V	6.0		
Discharge Temperature ²	°C	25°C	-20	+60

Protection Devices	N.B: These devices are designed to protect the pack in event of failure or abuse. Creasefield Flowmeter Batteries use non-rechargeable lithium batteries. Do not attempt to charge. Do not short circuit battery terminals. Polyswitch devices act as a self-resetting fuse.			
PCM Part No.		Polyswitch	16R185BU	
Fuse	none	Bypass Diode	1N5817	
Thermal Fuse	none	Reverse Current Protection Diode	1N5817	

creasefield.co.uk

© Copyright Creasefield Ltd 2013. This product design is the intellectual property of Creasefield Ltd. No design may be copied or used for commercial purposes without written permission of Creasefield Ltd. Users must satisfy themselves, by suitable testing, that products are fit for purpose. Data in this document is for general guidance only - consult Creasefield Ltd for information specifically relating to your application. Information is given free of charge and in good faith, but no responsibility can be accepted for errors, omissions, costs, losses or liabilities arising from the use of this information. Do not use in life critical applications.



Creasefield Ltd

Unit I Larchfield Estate Ilminster, Somerset TAI9 0PF

т 01460 54800 F 01460 57201

enquiries@creasefield.co.uk creasefield.co.uk

Product # CB18984	Issue #		Origination Date 08/05/2013	Originator Patrick Smith	Page # 2/2
Battery Specification	Nominal Ratings: 10.8v, 57Ah			Composition: 3S3P	

NB: Actual voltage and capacity in use will be affected by various factors, including temperature, discharge rate, charge rate and method (if applicable), end point voltage, history (e.g. past use, storage) etc.



Outline safety warning: Use only within the allowed parameters.

Do not short circuit the battery. Only use with ABB Flowmeter 3 equipment and in line with Flowmeter 3 instructions. Do not heat. Do not use above maximum temperatures indicated. Never crush, mutilate, puncture or abuse the battery. Do not dismantle the pack or disable any of the protective devices.



You should also consult the following documents:

- 1) Tadiran SL2780 Cell Data Sheet.
- 2) Material Safety Data Sheet.



Do not connect multiple packs in series or parallel.



Do not use the battery if you suspect it may be faulty or damaged.



Do not attempt to charge the battery.

Storage: Cell level testing indicates a capacity loss of approx. 2% per year in nominal storage conditions. Elevated temperatures will increase capacity loss. Batteries must be stored in a cool, dry area out of direct sunshine. Prolonged storage at high temperatures will shorten battery life.

New transport regulations affecting lithium, lithium-ion and/or lithium polymer batteries came into force during 2003 and 2004.

These regulations require that all lithium, lithium-ion and lithium polymer cells and batteries must pass a number of UN tests before they may be transported by road, rail, sea or air. In addition lithium, lithium-ion and lithium polymer cells and batteries containing more than certain limits of lithium or

"lithium equivalence" must be shipped as Class 9 hazardous goods. For cells and batteries containing lithium metal the classification is UN3090. Batteries below these limits may be transported as non-hazardous. There are certain exceptions.

Disclaimer: We do not claim to be experts in regard to transport regulations, shipping, packing etc. Users and prospective users of lithium, lithium-ion and/or lithium polymer cells and/or battery packs should consult a qualified person for definitive information, e.g. a Dangerous Goods Safety Advisor. Creasefield Ltd, its owners, directors, employees and servants cannot accept any responsibility for the accuracy of the above information.

- I Design life is dependent on usage and environment. Elevated temperatures will shorten battery life.
- 2 The battery may need to be derated at high and low temperatures. In particular, low temperatures will lower voltage response. High temperatures will increase self discharge and reduce battery life. See Tadiran SL2780 Data Sheet for further information.

creasefield.co.uk

© Copyright Creasefield Ltd 2013. This product design is the intellectual property of Creasefield Ltd. No design may be copied or used for commercial purposes without written permission of Creasefield Ltd. Users must satisfy themselves, by suitable testing, that products are fit for purpose. Data in this document is for general guidance only - consult Creasefield Ltd for information specifically relating to your application. Information is given free of charge and in good faith, but no responsibility can be accepted for errors, omissions, costs, losses or liabilities arising from the use of this information. Do not use in life critical applications.